



Bridging the Gap between Real World and Computer


Mokon-K Servo Driver



Features

- ▶ Embedded floating point DSP
- ▶ High bandwidth and high response
- ▶ Easy servo parameters setting via RS-232 communication with KSDT software or build-in operator's panel
- ▶ Selection of electronic gear from I/O signal or parameter
- ▶ On the fly change of torque, speed and position mode
- ▶ Multi-purpose type command input to support most of motion control applications.

Ordering Information



Specifications

- ▶ System Overload capacity : 150% 1min
- ▶ Discharge Transistor : integrated
- ▶ Protective Function : Over Current, Over Voltage, Low Voltage, Over Load, Over Temperature, Encoder Error, Over Speed
- ▶ Feedback Output : parameter programmable
- ▶ Heat-Dissipation Method : Natural ventilation

Speed Control:

- ▶ Control Method : Sine PWM Current Control
- ▶ Control Ratio : 3000:1
- ▶ Speed Command : 0~10V/0~Rated Speed
- ▶ Acceleration and Deceleration Method : S type or Linear type profile
- ▶ Torque Limit : 0~10V/0~300%Max Torque

Position Control:

- ▶ Position command : A/B, CW/CCW, PULSE/DIR
- ▶ Position command Output bandwidth : Differential type : 2M Transistor type : 200K
- ▶ Position Command Resolution : 4x Installed encoder resolution
- ▶ In-Position setting range : 0 ~ ±32767 pulse
- ▶ Electronic Gear Ratio : 1~2¹⁷
- ▶ Torque Limit : 0~10V/0~300%Max Torque

Torque Control:

- ▶ Torque command : 0~10V/300% Rated Torque
- ▶ Speed Limit : Internal Torque Speed limited or limit from External Analog Speed Limit Command



Environment:

- ▶ Storage Temperature : -20 °C ~ 65 °C
- ▶ Operation Temperature : 0 °C ~ 40 °C
- ▶ Humidity : Humidity below 90% RH, non-condensing
- ▶ Altitude : Sea Level below 1000M
- ▶ Vibration : Below < 5m/s



Bridging the Gap between Real World and Computer


Dimensions





Bridging the Gap between Real World and Computer

Control Interface




Note



Bridging the Gap between Real World and Computer

Control Interface



Speed Mode

Note

